

# Voice Control System

## REDIALLING

The commands

**>>Phone<<**

**>>Redial<<**

dial the telephone number last used.

### Command list

User command	System response
Phone	Phone
Redial	Confirm Yes or No
Yes	Dialling

## STORING A TELEPHONE NAME/NUMBER

Telephone numbers which you dial frequently can be stored in the Voice Recognition phone directory in conjunction with the contact's name.

### Storing via voice command

The command

**>>Phone<<**

**>>Store name<<**

starts the dialogue for storing a name. The name is entered first, then the number.

The same rules for saying numbers apply as for dialling a number.

If possible, keep names acoustically distinct from one another, for example, **"Andrew Royd"** and **"David Royle"** instead of **"Mr Royd"** and **"Mr Royle"**. This will improve recognition when you make a call.

Depending on the spoken length of the names and numbers you have entered, it is possible to store approximately 20 entries.

### Command list

User command	System response
Phone	Phone
Store name	Name please
Andrew Royd	Andrew Royd Storing name Number please
Zero, one, six, one	Zero, one, six, one, continue?
Four, nine, six	Four, nine, six, continue?
Zero, nine, nine, eight	Zero, nine, nine, eight, continue?
Store	Number Stored