

# Voice Control System

## USING THE VOICE RECOGNITION PHONE DIRECTORY

### Dialling a telephone number in phone directory

The commands

>>Phone<<

>>Dial name<<

activate the phone number in the  
directory corresponding to the name tag.

When prompted by the voice control  
system, speak the name under which you  
have stored the telephone number you  
want.

The voice control system will understand  
best the person who made the entries.

### Command list

User command	System response
Phone	Phone
Dial name	Name please
Andrew Royd	Andrew Royd, Confirm Yes or No
Yes	Dialling

### Playing the phone directory

The commands

>>Phone<<

>>Play directory<<

enable you to have all entries in your voice  
recognition phone directory read out in  
order.



You may cancel the playback of the  
directory at any time by pressing the  
'Telephone/Voice recognition'  
switch

### Command list

User command	System response
Phone	Phone
Play directory	<i>(Reads out the entries)</i>

# Voice Control System

---

## **Deleting/Clearing the entire phone directory**

The commands

**>>Phone<<**

**>>Delete directory<<**

will delete all entries in the Voice Recognition phone directory.

The names and telephone numbers entered in your Voice Recognition phone directory are independent of the telephone or SIM card memory of your phone. In other words, it is not possible to recall or delete the numbers stored in the telephone itself or on the SIM card by voice input, nor is it possible to store numbers there by voice input.

## **Command list**

<b>User command</b>	<b>System response</b>
Phone	Phone
Delete directory	Delete directory, Confirm Yes or No
Yes	Directory deleted