

Voice Control System

USING THE VOICE RECOGNITION PHONE DIRECTORY

Dialling a telephone number in phone directory

The commands

>>Phone<<

>>Dial name<<

activate the phone number in the
directory corresponding to the name tag.

When prompted by the voice control
system, speak the name under which you
have stored the telephone number you
want.

The voice control system will understand
best the person who made the entries.

Command list

| User command | System response |
|--------------|-----------------------------------|
| Phone | Phone |
| Dial name | Name please |
| Andrew Royd | Andrew Royd, Confirm Yes or No |
| Yes | Dialling |

Playing the phone directory

The commands

>>Phone<<

>>Play directory<<

enable you to have all entries in your voice
recognition phone directory read out in
order.



You may cancel the playback of the
directory at any time by pressing
the 'Telephone/Voice recognition'
switch

Command list

| User command | System response |
|----------------|--------------------------------|
| Phone | Phone |
| Play directory | <i>(Reads out the entries)</i> |

Voice Control System

Deleting/Clearing the entire phone directory

The commands

>>Phone<<

>>Delete directory<<

will delete all entries in the Voice Recognition phone directory.

The names and telephone numbers entered in your Voice Recognition phone directory are independent of the telephone or SIM card memory of your phone. In other words, it is not possible to recall or delete the numbers stored in the telephone itself or on the SIM card by voice input, nor is it possible to store numbers there by voice input.

Command list

| User command | System response |
|------------------|--|
| Phone | Phone |
| Delete directory | Delete directory, Confirm Yes or No |
| Yes | Directory deleted |